

Ferromagnetic 35 W transformer with terminal connection at primary and secondary side

320-00002

4 year warranty

This ferromagnetic transformer has a capacity of 35W. It is suitable for use with low-voltage loads (12 V LED). These lamps can then be dimmed with phase control and universal dimmers. The transformer has two screw terminals for connection, at both primary and secondary side. This transformer is also suitable for flush-mounting in furniture. It is equipped with an integrated thermal protection and an integrated protection against short-circuit, overload and overheating. The transformer has an IP20 protection degree.



Technical data

Ferromagnetic 35 W transformer with terminal connection at primary and secondary side

- Function: ferromagnetic transformer
- Input voltage: 230 Vac \pm 10 %, 50 Hz
- Dimensions (HxWxD): 36 x 182 x 41 mm
- Primary wire connection: double primary terminal connection: 1 x 6 mm² per screw terminal
- Secondary wire connection: double secondary terminal connection: 2 x 6 mm² per screw terminal
- Number of exits (pairs): 1
- Output voltage: 11.5 Vac, 50-60 Hz
- Maximum load: 35 W
- Application: suitable for flush-mounting in furniture
- Mounting method: flush-mounting
- Safety protections: resettable protection against overload and overheating (interrupt the voltage to reactivate protection)
- Protection degree: IP20
- Protection class: Class III device: SELV (safety extra low voltage), suitable as a power supply for class III loads
- Finishing colour: black
- Material upperframe: plastic
- Certification marks: ENEC
- Marking: CE
- Weight: 1000 g



niko

Dimensions

