

Product Code: FPSS751WH

Description: 13A Ingot Double Pole Switched Fused Connection Unit

**General Information**

|                                        |                                             |                                          |
|----------------------------------------|---------------------------------------------|------------------------------------------|
| Plate Dimensions (mm)                  | 86 (W) x 86 (H) x 1.3 (D)                   |                                          |
| Dimensions With Gasket (mm)            | 86 (W) x 86 (H) x 3 (D)                     |                                          |
| Plate Fixing Centres - Horizontal (mm) | 60.3                                        |                                          |
| Style                                  | Flat Plate                                  |                                          |
| Finish                                 | Stainless Steel                             |                                          |
| Insert Colour                          | White                                       |                                          |
| Gasket Colour                          | Transparent (Neoprene)                      |                                          |
| Materials                              | Front Plate: Stainless Steel                | Insert & Housing: Urea                   |
|                                        | Switch & Fuse Drawer Cover: Stainless Steel | Terminals: Brass                         |
|                                        | Terminal Screws: Steel & Yellow Passivated  | Contacts: Silver "on-lay" Copper / Brass |
|                                        | Internal Busbars: Formed Pressed Brass      | Earth Strap: Mild Steel                  |
| Anti Microbial Certified               | No                                          |                                          |
| Rated Voltage (V~) (Ue)                | 250                                         | Frequency (Hz) 50                        |
| Resistive Load Rating (A)              | 13                                          |                                          |
| Fuse Fitted Rating & Type              | 13A (BS 1362)                               |                                          |
| Termination Type                       | Screw                                       |                                          |
| Terminal Size (mm)                     | Ø5                                          | Terminal Torque Value (Nm) 2             |
| Terminal Capacity - Solid (mm²)        | 3 x 2.5 or 2 x 4                            |                                          |
| Switched                               | Yes                                         |                                          |
| Double Pole Switch                     | Yes                                         |                                          |
| Twin Earth Terminals                   | Yes                                         |                                          |
| Product Marking                        | Fused                                       |                                          |
| Minimum Back Box Depth (mm)            | 35                                          |                                          |
| Ingress Protection                     | IP20                                        |                                          |
| Operational Temperature (°C)           | -5 to +40                                   |                                          |
| Warranty (Years)                       | 10                                          |                                          |
| Standards                              | BS 1363-4<br>BS 1362                        |                                          |

**Additional Information**

For cleaning / polishing of products, use only a soft, dry, clean cloth.  
Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.  
Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.