



# PIR Sensor

Passive infra-red motion sensor with daylight threshold switch

| Features        |                     | Installation information    |                |
|-----------------|---------------------|-----------------------------|----------------|
| IP rating       | IP65                | Install Connector Type      | Zhaga Book 18  |
| Dimmable Option | Yes (0-10V and PWM) | Weight                      | 0.03           |
|                 |                     | Maximum Ambient Temperature | -20°C to +60°C |

## Accessories

|          |                        |                 |
|----------|------------------------|-----------------|
| Area Bay | High bay product range | Sold Separately |
|----------|------------------------|-----------------|

## PRODUCT CODES

|       | Finish             | Description                                                          |
|-------|--------------------|----------------------------------------------------------------------|
| HBPIR | Matt black RAL9017 | Passive infra-red (PIR) motion sensor with daylight threshold switch |



collingwood

01604 495 151  
collingwoodlighting.com

- collingwoodled
- /collingwoodlighting
- collingwoodlighting

## Guarantee

5 years

## Features & benefits

Plugs into the centre of the Area Bay luminaire using the Zhaga socket

Typical installation height 8-13m

Hold time  
Default is 5 seconds  
Options -  
30s/1min/3min/5min/10min/20min/30min

Stand-by dimming level  
Default is 10%  
Options - 20%/30%/50%

Stand-by period  
Default is 0 seconds  
Options -  
10s/30s/1min/5min/10min/30min

Daylight threshold  
Default is 'disable'  
Options -  
2Lux/10Lux/30Lux/50lux  
120Lux/200Lux/250Lux  
300Lux/350Lux/400Lux