

Product name

LAVA-DIMM-LED

Item number

40467

Manufacturer

ETHERMA



Product description

Dimmer for lighting LAVA-LED, suitable for all sizes

The radio-controlled dimmer can be used to dim the LAVA-LED lighting. Can be controlled either wired via pushbutton or via the radio hand-held transmitter LAVA-FHS-LED. The dimmer can be used for all LAVA-LED sizes. protection rating: IP 20
Dimensions: 95 x 37 x 20 mm, radio frequency: 868 mHz, maximum output line: 192W, output current: 1 x 8A

Technical Details

Assembly arrangement	Basic element with complete housing	Number of modules (module system)	0
Method of operation	Radio frequency (RF)	RAL-number (similar)	9016
App control via Bluetooth	No	Nominal voltage	12 12 Volt
Dimming phase cut-on	Yes	Frequency	0 0 Hertz
Dimming phase cut-off	No	Control voltage	12 12 Volt
Serial dimmer	No	Nominal power resistive load	96 192 Watt
Type of load	Universal	Nominal power inductive load	96 192 Voltampere
Substation input	Yes	Nominal power capacitive load	96 192 Voltampere
Light value memory	Yes	Max. switching power LED	0 Watt
Applicable with button	Yes	Core cross section	1.5 1.5 Square millimetre
Applicable with movement sensor	Yes	Device width	37 Millimetre
Applicable with presence indicator	Yes	Device height	100 Millimetre
Applicable with time switch/timer	Yes	Device depth	21 Millimetre
Applicable with transmission button	Yes	Min. depth of built-in installation box	0 Millimetre
Applicable with infrared button	No		
Mounting method	Surface mounted		
Type of fastening	Mounting with screw		
Material	Plastic		
Material quality	Thermoplastic		
Halogen free	No		
Surface protection	Untreated		

Surface finishing	Matt
Colour	White
Transparent	No
Suitable for degree of protection (IP)	IP20
Impact strength	IK01
Connection type	Screw terminal
Compatible with Apple HomeKit	No
Compatible with Google Assistant	No
Compatible with Amazon Alexa	No
IFTTT support available	No