

Product name

ET-111C

Item number

40039

Manufacturer

ETHERMA



Product description

Radio receiver for LAVA LITE, in flush-mounted box, 10A

The ET-111C radio receiver enables easy switching on of electric heaters as well as floor heating systems. The receiver can control the room temperature with the ET-14A device, as well as the floor temperature in conjunction with the ET-EF-111 remote sensor. The frequency range 868 MHz guarantees a large range and optimal connection. Mounting in flush box, switching current: 10 A, dimensions: 50x47x33 mm, protection rating: IP 20, transmission frequency: 868 MHz, range 100 - 300 m, CE marking.

Technical Details

Suitable for dimmer	No	Number of relays	1
Suitable for pulse button	No	RAL-number (similar)	9016
Suitable for roller shutter switch	No	Radio frequency	868 Megahertz
Suitable for venetian shutter switch	No	Code length (Bit)	0
Suitable for venetian-/roller shutter switch	No	Number of commands	0
Suitable for switch	Yes		
In housing	No		
In tube base housing	No		
Printed circuit board/module	Yes		
Current supply	230 V AC		
Push button mode	No		
Switching mode	Yes		
With manual radio transmitter	No		
With radio coding device	No		
With radio controlled push button	No		
Mounting method	Flush-mounted		
Material	Plastic		
Material quality	Duroplast		
Halogen free	No		
Surface protection	Untreated		
Surface finishing	Matt		
Type of fastening	Mounting with screw		

DATASHEET.

Colour	White
Transparent	No
Suitable for degree of protection (IP)	IP20
Degree of protection (NEMA)	Other
Modulation	FM
Rolling code system	No
Compatible with Apple HomeKit	No
Compatible with Google Assistant	No
Compatible with Amazon Alexa	No
IFTTT support available	No