

Nom du produit


ET-111A

Numéro de l'article

36758

Fabricant

ETHERMA

**Description du produit**

Récepteur sans fil ET-111A pour LAVA 16A

Le récepteur sans fil ET-111A peut être facilement monté sur le LAVA BASIC-DM et appris avec un ET-14A.

Détails techniques

Suitable for dimmer	No	Number of relays	1
Suitable for pulse button	No	RAL-number (similar)	9010
Suitable for roller shutter switch	No	Radio frequency	868 Megahertz
Suitable for venetian shutter switch	No	Code length (Bit)	0
Suitable for venetian-/roller shutter switch	No	Number of commands	0
Suitable for switch	No		
In housing	Yes		
In tube base housing	No		
Printed circuit board/module	No		
Current supply	230 V AC		
Push button mode	No		
Switching mode	Yes		
With manual radio transmitter	No		
With radio coding device	No		
With radio controlled push button	No		
Mounting method	Other		
Material	Plastic		
Material quality	Thermoplastic		
Halogen free	Yes		
Surface protection	Untreated		
Surface finishing	Matt		
Type of fastening	Other		
Colour	White		
Transparent	No		

FICHE-TECHNIQUE.

Suitable for degree of protection (IP)	IP20
Degree of protection (NEMA)	Other
Modulation	FM
Rolling code system	No
Compatible with Apple HomeKit	No
Compatible with Google Assistant	No
Compatible with Amazon Alexa	No
IFTTT support available	No