

# Ferromagnetic 300W block transformer (with terminal connections)

320-00006

4 year warranty

This block transformer has a capacity of 300W. It is suitable for use with low-voltage loads (12 V LED). These lamps can then be dimmed with phase control and universal dimmers. The transformer is connected using two screw terminals at primary side and four screw terminals at secondary side. It has an IP20 protection degree. The attachment brackets are supplied.

## Technical data

Ferromagnetic 300W block transformer (with terminal connections)

- Function: ferromagnetic transformer
- Input voltage: 230 Vac  $\pm$  10 %, 50 Hz
- Dimensions (HxWxD): 160 x 135 x 115 mm
- Primary wire connection: double primary terminal connection: 1 x 6 mm<sup>2</sup> per screw terminal
- Secondary wire connection: Fourfold secondary terminal connection: 4 x 6 mm<sup>2</sup> per screw terminal
- Number of exits (pairs): 2
- Output voltage: 11.5 Vac, 50-60 Hz
- Maximum load: 300 W
- Mounting method: surface mounting
- Protection degree: IP20
- Protection class: Class III device: SELV (safety extra low voltage), suitable as a power supply for class III loads
- Finishing colour: black
- Material upperframe: plastic
- Marking: CE
- Weight: 6300 g



CE

**niko**

320-00006 - 15-06-2023

