

Safety Pendant & Battens

Description

This range of Safety Lampholder and Pendant Set allows for the removal of lamps without leaving live exposed points in the lampholder.



Features

- T2 rated lampholders
- B22 bayonet lampholders
- Unique shutter and retractable pin mechanism when the lamp is removed, ensuring safety
- 3 terminals
- Decorator Safety Cover
- 10-year guarantee

Technical Specification

Voltage rating 230Vac
Wattage rating 150W

No user serviceable parts

Range

Safety straight batten holder – Home Office Skirt	S96HOT2
Safety angled batten holder – Home Office Skirt	S97HOT2
6" Safety Pendant – White base	S1066T2

Terminal Capacity

	1mm ²	1.5mm ²
L & N	5	3

Lamp Replacement

Safety lampholders have a unique shutter action which retracts and shields the contact pin when the lamp is removed.

To remove lamp, push the lamp up into the lamp holder and twist anticlockwise. An audible click will be heard when the pins have retracted into the lamp holder. Pull the lamp gently out of the lampholder.

To replace the lamp, line up the horizontal pins on the lamp with the slots in the lamp holder. Firmly push the lamp into the lampholder and twist clockwise until an audible click is heard. This click is the pins moving into position and making contact with the lamp.

Standards

- BS EN 61184,BS67
- BS 7895