

Product datasheet

Specifications

extended relay module - 3 relays



VW3A3204

EAN Code: 3606480702532

Main

Product or component type	Additional output module
Range compatibility	Altivar Machine ATV340 Easy Altivar 610 Altivar Process ATV900 Altivar Process ATV600
Input/output type	3 relay output
Discrete output number	3
Discrete output type	(R4, R5, R6) relay normally open, sampling time: 1 ms

Complementary

Electrical durability	100000 cycles
Minimum switching current	5 mA at 24 V DC
Maximum switching current	2 A at 250 V AC on inductive load, $\cos \phi = 0.4$ and $L/R = 5$ ms 2 A at 30 V DC on inductive load, $\cos \phi = 0.4$ and $L/R = 5$ ms 5 A at 250 V AC on resistive load, $\cos \phi = 1$ and $L/R = 5$ ms 5 A at 30 V DC on resistive load, $\cos \phi = 1$ and $L/R = 5$ ms
Electrical connection	Screw terminal block, 1.5 mm ² / AWG 16, 0.5 N.m
Net weight	0.4 kg

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	6.5 cm
Package 1 Width	13.0 cm
Package 1 Length	19.0 cm
Package 1 Weight	152.0 g
Unit Type of Package 2	S03
Number of Units in Package 2	16
Package 2 Height	30.0 cm
Package 2 Width	30.0 cm
Package 2 Length	40.0 cm
Package 2 Weight	3.114 kg

Logistical informations

Country of origin	ID
-------------------	----

Contractual warranty

Warranty

18 months

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard

No

Packaging without single use plastic

No

[EU RoHS Directive](#)

Pro-active compliance (Product out of EU RoHS legal scope)

SCIP Number

2a2f2e41-9976-44a1-aaef-cecaebe1de88

REACH Regulation

[REACH Declaration](#)

Use Again

Repack and remanufacture

End of life manual availability

No need of specific recycling operations

Take-back

No