

Norsk versjon




Svensk version



Detection range

Sensor sensitivity can be adjusted by selecting the combination on the DIP switches to lit precisely for each specific application.


	1	2	3	
I	●	●	●	100%
II	○	●	●	75%
III	●	○	●	50%
IV	●	●	○	30%
V	○	○	○	10%



Hold period

The Hold period is the time you would like to keep the light on 100% after the person has left the detection area.

	1	2	3	
I	●	●	●	5 sec
II	○	●	●	30 sec
III	●	○	●	3 min
IV	○	○	●	5 min
V	●	●	○	15 min
VI	○	○	○	25 min



Daylight threshold

The Daylight threshold can be set on DIP switches to fit for the particular application.
 "daylight" - always in operation, night and day
 "twilight" - operate in twilight and darkness
 "darkness" - operate on darkness only

The Daylight Threshold has a 5 min delay.

	1	2	3	
I	●	●	●	2 lux - darkness operation only
II	○	●	●	5 lux - darkness operation only
III	●	○	●	20 lux - twilight operation
IV	○	●	○	30 lux - twilight operation
V	○	○	○	daylight - sensor disabled

