

# Ei129



## Switched Input Module



- Triggers the alarms in a system if an external device is activated, such as a sprinkler flow switch
- Mains powered with Rechargeable Lithium Back-up
- Connects with the alarm system through a hard wire interconnect
- Compatible with the 3000, Ei2110e Multi-Sensor Fire Alarm, 160e Series alarms and the 140RC Series

## Description

The Ei129 Switched Input Module will trigger interconnected alarms if an external device is activated, such as a sprinkler system. It is mains powered with rechargeable lithium back-up and is compatible with 3000, 2110e, 160e and 140RC Series alarms

## Technical

<b>Supply Voltage (V)</b>	230	<b>Voltage Type</b>	AC
<b>Battery Type</b>	Lithium rechargeable	<b>Power Consumption (W)</b>	0.2

## Dimensions & Weights

<b>Depth (mm)</b>	30	<b>Height (mm)</b>	145
<b>Width (mm)</b>	145	<b>Product weight (kg)</b>	0.170
<b>Packaged weight (kg)</b>	0.204		

## Approvals & Warranty

<b>Certification/Approvals</b>	EN 60065:2014, EN 61000-6-1:2007, EN 61000-6-2:2005	<b>Warranty</b>	5 year warranty
<b>EAN Number</b>	5099383004878		

## Environmental

<b>Humidity Range (%)</b>	15-95	<b>Temperature Range (°C)</b>	-10 to 40
---------------------------	-------	-------------------------------	-----------