



collingwood

01604 495 151
collingwoodlighting.com

-  collingwoodled
-  /collingwoodlighting
-  collingwoodlighting



LEDEP11

Emergency converter for H2 and H4 Pro, self-test, maintained.

Features

IP rating	IP20
-----------	------

Installation information

Install Connector Type	Mains: Push-fit terminals 0.5 - 2.5mm ² DC: Plug & Play connectors
Cut Out Size	Ø18mm (status LED) / Ø7mm (test button)
Inrush Current	10A
Construction Material	Polycarbonate
Weight	294g
Maximum Ambient Temperature	0 to 50°C
SELV	Yes
Electric Class (1, 2, 3)	2

Guarantee

3 year extended guarantee

Features & benefits

- Self-test device, simplifying the emergency lighting inspections
- Dual colour Green / Red LED status indicator
- A minimum of 3 hours of emergency lighting
- Built-in protection:
 - open circuit
 - over charging
 - over discharging
 - over temperature
- LiFePO₄, provides long operational life
- Supplied with a test button, whereby a battery duration test can be carried out at anytime
- Synchronizes an automatic battery duration test every 6 months
- Compatible with our H2 and H4 Pro colour and lumen switchable downlights

Wiring information

Cable / Flying Lead	Plug & Play connectors
Type of Wiring Required	Parallel

Accessories

No accessories required

PRODUCT CODES

	Finish	Description	Characteristic 1	Characteristic 2
LEDEP11	White	Emergency converter for H2 and H4 Pro, Self-test, maintained.	LiFePO ₄ battery	6.4V 1500mAh

