


Accessories Contd.

'Monobloc'

The Monobloc assembly is designed for use in very restricted space. The contacts are assembled in the base of the actuator and cannot be supplied separately. To replace the contacts will require a new complete actuator.

Catalogue No. **FVRKOO**



Contact Block, Momentary Action 2 N/C

Electrical Ratings - BS EN 60947-5-1

	a.c.
Utilisation Category	AC15 B300
Rated Insulation Voltage (Ui)	250V
Rated Operational Voltage (Ue)	240V / 120V
Rated Operational Current (Ie)	1.5A / 3A
Breaking Capacity	10Ie
Continuous thermal current (Ith)	5A


'S1' Series

The S1 contact block is designed to be stacked in pairs side-by-side and then back-to-back making a total on four changeover blocks on one Heavy Duty actuator. Three or four blocks will require extended fixing screws (U42)

Catalogue No. **S1**



Image shows
2 off S1 blocks



Contact Block, Momentary Action C/O

Electrical Ratings - BS EN 60947-5-1

	a.c.
Utilisation Category	AC15
Rated Insulation Voltage (Ui)	660V
Rated Operational Voltage (Ue)	400V
Rated Operational Current (Ie)	5A
Continuous thermal current (Ith)	10A

Catalogue No. **U42**

Assembly screw kit to enable 3 or 4 'S1' contacts to be mounted on a single Heavy Duty actuator.

Mechanical Endurance:-

All **HD** assemblies with the exception of Emergency Stops

HD Emergency Stop (Twist-to-reset & pull-to-reset)

All **ND** assemblies

1x10⁶ operations

0.25x10⁶ operations

1x10⁶ operations

"Over 60 years experience in design and manufacture"

