



Fully compatible with Scantronic i-on range. Eaton's SDR-RINT internal sounder enables tidier wire-free domestic installation. Offering the option of connecting via either a radio expander or control unit with built-in radio capability.

The internal sounder is ideal for those hard-to-reach areas out of earshot of keypads or panels - but where users need to hear system sounds. Designed with a discreet housing, the unit blends in easily in entrance halls and other aesthetically sensitive areas.

### At a glance...

- 2 way radio
- Uses 4 x AA batteries
- 80dB output
- All system sounds including entry/exit, fault and alarm tones
- Multiple internal radio sounders can be put on the same system
- Compatible with all i-on control panels with v4.05 software or higher and if applicable, radio expander software v2.09 or higher
- Third party certified to EN50131 Grade 2

### Variants

Part No	Description
SDR-RINT	Radio internal sounder

### Compatibility

	Description
i-on30R	Panel end station
i-on40H	Panel end station
EXP-R10	10 zone radio expander
EXP-R30	30 zone radio expander
Style	40 zone integrated panel
Compact	20 zone integrated panel

### Technical specification

External Supply	12Vdc (optional)
Cut-off Period	Auto-silences after 3 minutes if powered only by batteries
Battery Type	4 x 1.5Vdc AA alkaline
Battery Life	Typically >12 months when powered only by batteries, assuming a total of 80 seconds per day of entry/exit tones
Weight	275g (with batteries)
Dimensions H x W x D (mm)	127 x 127 x 40