Data Sheet | Item Number: 280-485

Jumper; 5-way; insulated; gray

https://www.wago.com/280-485



Color: gray

Similar to illustration

Technical data	
Number of spacings	5 -times

Electrical data	
Rated current	24 A

Physical data	
Width	25 mm / 0.984 inches
Height	4 mm / 0.157 inches
Depth	19.2 mm / 0.756 inches

Material data	
Color	gray
Fire load	0.015 MJ
Weight	2.5 g

Commercial data	
PU (SPU)	100 (25) pcs
Packaging type	Box
Country of origin	DE
GTIN	4045454083519
Customs tariff number	85366990990

Product Classification

UNSPSC	39121421
eCl@ss 10.0	27-14-11-40
eCl@ss 9.0	27-14-11-40
ETIM 9.0	EC000489
ETIM 10.0	EC000489
ECCN	NO US CLASSIFICATION

Environmental Product Compliance

RoHS Compliance Status	Compliant,No Exemption

Downloads

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 280-485

Documentation

Bid Text

280-485	27.04.2017	doc 24.00 KB	
280-485	19.02.2019	xml 2.54 KB	

CAD/CAE-Data

CAD data

2D/3D Models 280-485

CAE data

EPLAN Data Portal 280-485

WSCAD Universe 280-485

ZUKEN Portal 280-485

Continued on next page

1 Compatible Products

1.1 Optional Accessories


1.1.1 Tool

1.1.1.1 Operating tool


Item No.: 280-435
Operating tool; made of insulating material; 5-way; gray

Installation Notes

Commoning



Insert push-in type jumper bar and push down until it hits backstop.



Removing a push-in type jumper bar:
Insert the operating tool between the jumper and partition wall of the dual jumper slots, then lift up the jumper.
Place the operating tool in the center of jumpers for up to five contacts (see above), or alternately on both sides for jumpers with more than five contacts.

Commoning




Custom jumpers are created by breaking and removing jumper contacts (2000, 2001, 2002, 2004 Series).




Marking with a felt-tip pen.


Commoning




Stepping down via push-in type jumper bar.



Stepping down via push-in type jumper bar:
Commoning via closed terminal side with end plate allows jumpering over two cross-section sizes, e.g., from 16 mm² (6 AWG) to 6 mm² (10 AWG) or from 6 mm² (10 AWG) to 2.5 mm² (14 AWG) (see illustration above).



Stepping down via push-in type jumper bar:
Commoning via open terminal side with end plate allows jumpering over two cross-section sizes for 16 mm² (6 AWG) and 10 mm² (8 AWG) and one cross-section size for 6/4/2.5 mm² (10/12/14 AWG). An example: from 16 mm² (6 AWG) to 6 mm² (10 AWG) (see illustration above) or from 10 mm² (8 AWG) to 4 mm² (12 AWG).



Note:
The total current of the outgoing circuits must not exceed the nominal current of the step-down jumper/push-in type jumper bar.