Data Sheet | Item Number: 280-492

Jumper; 2-way; insulated; gray

https://www.wago.com/280-492



Color: gray

Technical data	
Number of spacings	2 -times

Electrical data	
Rated current	24 A

Physical data	
Width	13.8 mm / 0.543 inches
Height	4 mm / 0.157 inches
Depth	19.2 mm / 0.756 inches

Material data	
Color	gray
Fire load	0.008 MJ
Weight	1.1 g

Commercial data	
PU (SPU)	200 (25) pcs
Packaging type	Box
Country of origin	DE
GTIN	4045454027070
Customs tariff number	85366990990

Continued on next page

Product Classification

UNSPSC	39121421
eCl@ss 10.0	27-14-11-40
eCl@ss 9.0	27-14-11-40
ETIM 9.0	EC000489
ETIM 10.0	EC000489
ECCN	NO US CLASSIFICATION

Environmental Product Compliance

RoHS Compliance Status	Compliant,No Exemption

Downloads

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 280-492

Documentation

Bid Text

280-492	30.05.2017	doc 24.00 KB	
280-492	19.02.2019	xml 2.57 KB	

CAD/CAE-Data

CAD data

2D/3D Models 280-492

CAE data

EPLAN Data Portal 280-492

WSCAD Universe 280-492

ZUKEN Portal 280-492

Continued on next page

1 Compatible Products

1.1 Optional Accessories

1.1.1 Tool


1.1.1.1 Operating tool




Item No.: 280-433
Operating tool; made of insulating material; 3-way; white

Installation Notes

Commoning



Insert push-in type jumper bar and push down until it hits backstop.



Removing a push-in type jumper bar:
Insert the operating tool between the jumper and partition wall of the dual jumper slots, then lift up the jumper.
Place the operating tool in the center of jumpers for up to five contacts (see above), or alternately on both sides for jumpers with more than five contacts.

Commoning




Custom jumpers are created by breaking and removing jumper contacts (2000, 2001, 2002, 2004 Series).




Marking with a felt-tip pen.


Commoning




Stepping down via push-in type jumper bar.



Stepping down via push-in type jumper bar:
Commoning via closed terminal side with end plate allows jumpering over two cross-section sizes, e.g., from 16 mm² (6 AWG) to 6 mm² (10 AWG) or from 6 mm² (10 AWG) to 2.5 mm² (14 AWG) (see illustration above).



Stepping down via push-in type jumper bar:
Commoning via open terminal side with end plate allows jumpering over two cross-section sizes for 16 mm² (6 AWG) and 10 mm² (8 AWG) and one cross-section size for 6/4/2.5 mm² (10/12/14 AWG). An example: from 16 mm² (6 AWG) to 6 mm² (10 AWG) (see illustration above) or from 10 mm² (8 AWG) to 4 mm² (12 AWG).



Note:
The total current of the outgoing circuits must not exceed the nominal current of the step-down jumper/push-in type jumper bar.