






## LED LINEAR LIGHT

<b>Item Code</b>	<b>CCT</b>		
521028003000	3000K/4000K	0.7Kg	

	<b>Model Name</b>	<b>L (mm)</b>	<b>D (mm)</b>	<b>H (mm)</b>	<b>Rated Voltage (V~)</b>	<b>Frequency (Hz)</b>	<b>Current (A)</b>	<b>Power Factor</b>	<b>Rated Power(W)</b>
	LEDLinear-Java L580-10W	580	72	66	220-240	50/60	0.3	0.9	10

### Light Source

Product Code	Product Description	N	Light source code	QR Code	Energy Label
521028003000	LEDLinear-Java L580-10W-830/840-WH	1	LS118001032		

\* This product contains a light source of energy efficiency class (C).

### Safety Instructions



To ensure correct function and safety, please read and follow all instructions carefully before using the product:

1. Turn off power supply before installation or before doing any maintenance work.
2. Do not install any luminaire near the heat source.
3. Do not exceed the nominal supply voltage or amperage ratings.
4. All wiring and installation of the light fitting must adhere to local and national wiring rules.
5. Take care not to pull any electrical wires during unpacking as this may damage the connection.
6. Lay out all the components on a smooth surface and make sure there are no components missing before assembling.
7. To avoid injury or damage to the fitting, please ensure that power leads and screws are secure before connecting the power.
8. Please keep instructions for future reference.
9. Please refer to IP(Ingress Protection) rating of this luminaire when deciding the location of installation.
10. If luminaire is exposed to high corrosive environment(coastal rigion), it will require a higher durability of powder coat, consult manufacturer before installation.

### Installation Procedure


#### WARNING

1. Switch off before installation.
2. Switch on only after complete installation and examination of the circuit.
3. Professional electrician for installation and maintenance only.




## Waterproof Installation Tips(If applicable)

### Waterproof gasket for screwing




Fasten the waterproof gasket into the mounting screws to prevent water from leaking inside.

### Waterproof grommet for cable entry




If there is gap between cable and waterproof grommet, please fill it with water-resistant silicone caulk to prevent water from leaking inside.

### Waterproof cable Gland for mains entry



Ensure that the waterproof cable gland is tightened to prevent water from leaking inside.

### Water-resistant silicone caulk in knock out hole



Caunks in knock out holes are tight enough to avoid dust, insects, and especially water from leaking inside.

## Wall mount installation

select preferred colour temperature for product in CCT change function only

**1**

spec	A
580mm	170mm

**2**

N Neutral  
 ⊕ Earth  
 L Switched

Wire diameter: 0.5-2.5mm<sup>2</sup>  
 Wire stripping length: 8-10mm

**3**


Align

**4**

**5**

COMPLETE

**6**



Opplé Lighting B.V.  
 Meerenaekerweg 1-07  
 5652 AR Eindhoven  
 The Netherlands  
 service@opple.com  
 www.opple.com

Data subject to change  
 Les données sont sujettes à modifications  
 Änderungen vorbehalten

OPPLE Lighting Co., Ltd.  
 Room 411, Building 1 No. 6111, Longdong Avenue,  
 Pudong New District, Shanghai City 201201, P. R. China