

## Electronic potentiometer

Product Data Sheet



Assembly arrangement	Basic element
Method of operation	Turn/push button
Type of load	Other
Mounting method	Other
Type of fastening	Other
Surface protection	Untreated
Colour	Other
Suitable for degree of protection (IP)	IP20
Serial dimmer	No
Substation input	No
Halogen free	Yes
Frequency	50-50Hertz

**Electronic potentiometer**

Electronic potentiometer for operating electronic ballasts and dimmers (PEHA REG dimmes page 15), with 1-10 V DC control voltage, max. control voltage 12 V DC, min. control voltage 1 V DC, max. control current 50 mA, switching contact max. 10 A, 230 V, max. 6 electronic ballasts directly switchable, rated current 4 A, fuse T 4 H 250 V

Material No.	Article No.	EAN-code
00210913	D 430 POT O.A.	4010105210910

---

**PEHA Elektro GmbH & Co.KG**

a Honeywell Company  
Daimlerstraße 4  
58553 HALVER  
DEUTSCHLAND

Tel.: 02353 9118 001  
Fax: 02353 9118 311  
mail: [peha@honeywell.com](mailto:peha@honeywell.com)  
[www.peha.de](http://www.peha.de)

Änderungen vorbehalten. © Honeywell PEHA