

PRODUCT DATASHEET

SMART+ Contact Sensor for WiFi products

SMART+ CONTACT SENSOR | SMART+ sensors with WiFi technology



Areas of application

- For indoor use only

Product benefits

- Notification of contact status change
- Monitors the history of contact status
- Easy control of compatible SMART+ WiFi products based on contact status

Product features

- Wireless smart contact sensor for status of windows and doors (open/close)
- Easy and flexible installation thanks to adhesive pad and wireless operation
- Rechargeable battery-powered (6 months lifetime per charging, 5 detections per day)
- Check the battery level by SMART+ WiFi APP
- Network protocol: WiFi

TECHNICAL DATA

Electrical data

Nominal voltage	3,7 V
Mains frequency	0 Hz

Dimensions & Weight



Product weight	47.00 g
Length	72.0 mm
Width	31.00 mm
Height	24.00 mm

Colors & materials

Product color	White
Body material	ABS

Temperatures & operating conditions

Ambient temperature range	-10...+50 °C
---------------------------	--------------

Capabilities

Dimmable	No
----------	----

Certificates & Standards

Type of protection	IP20
--------------------	------

EQUIPMENT / ACCESSORIES

- For control via LEDVANCE SMART+ WiFi App, a smart phone or Tablet PC is required (with minimum Android 4.4 or iOS 9.0)
- Rechargeable battery integrated
- Charging cable and installation kit included

DOWNLOAD DATA

DOWNLOAD DATA

DOWNLOAD DATA



User instruction



Declarations of conformity

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4058075730052	Folding box 1	62 mm x 80 mm x 98 mm	86.00 g	0.49 dm ³
4058075730069	Shipping box 4	173 mm x 108 mm x 141 mm	417.00 g	2.63 dm ³
4058075730076	Shipping box 32			

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.