

Remote control with 4 channels and 13 control keys

05-312

4 year
warranty

With this hand-held transmitter, you control a maximum of 52 circuits, independent of one another, but dependent on the receiver settings. You use the hand-held transmitter for 1-key, 2-key and 4-key functions. The operation status and channel selection is indicated with LEDs. This hand-held transmitter cannot be used in Niko Home Control installations.

Technical data

Remote control with 4 channels and 13 control keys

- Controls a maximum of 52 circuits, independent of one another
- LED indicates the channel selection and operation status
- Max. transmission range in a building: 30 m
- Max. transmission range in open field: 100 m
- Battery type: 2 x 3V CR2032 (meegeleverd) (supplied)
- Not compatible with the wireless bridge
- Communication protocol: Easywave®
- Maximum radio frequency power: -3.6 dBm
- Operating frequency: 868.3 GHz
- Dimensions (HxWxD): 151 x 61 x 21 mm
- Marking: CE

