

Base for wireless switch with 4 control buttons

410-00002


4 year
warranty

With this wireless switch, you control a maximum of 4 circuits, independent of one another, but dependent on the receiver settings. You use the switch for 1-key, 2-key and 4-key functions.

Technical data

Base for wireless switch with 4 control buttons.

- Each transmitter can control an unlimited number of receivers
 - Each receiver can be controlled by up to 32 transmitters
 - Transmission range: max. 30 meters indoors, 100 meters in the open area
 - Modulation type: FSK
 - Supplied complete with battery and pre-programmed send address
 - Buttons and faceplate to be ordered separately
 - Power supply: via battery 3 V DC (included)
 - Mounting: with the supplied adhesive strips or screws
 - frequency band: 868,0 – 868,6MHz
 - Possible to communicate with the connected controller by connecting the USB RF interface to a free USB port of the connected controller
 - Not compatible with the wireless bridge
 - Function: wireless switch/push-button dimmer
-
- Communication protocol: Easywave®
 - Maximum radio frequency power: -3.25 dBm
 - Operating frequency: 0.8683 GHz
 - Dimensions (HxWxD): 71 x 103 mm
 - Weight: 21 g
 - Marking: CE



Niko

Dimensions

