

The server returned a "500 Internal Server Error".

Something is broken. Please let us know what you were doing when this error occurred. We will fix it as soon as possible. Sorry for any inconvenience caused.

FICHA TÉCNICA DEL PRODUCTO ST 111 LONGLIFE

Starters for single operation at 230 V AC (ST 111, ST 171, ST 173) | Cebador para conexión individual en 230 V AC



Características del producto

- Margen de temperatura para desconexión segura: -20...+80 °C)

Oops! An Error Occurred

The server returned a "500 Internal Server Error".

Something is broken. Please let us know what you were doing when this error occurred. We will fix it as soon as possible. Sorry for any inconvenience caused.

The server returned a "500 Internal Server Error".

Something is broken. Please let us know what you were doing when this error occurred. We will fix it as soon as possible. Sorry for any inconvenience caused.

INFORMACION TECNICA

DATOS ELÉCTRICOS

Potencia nominal	65,00 W
Tensión nominal	220...240 V
Frecuencia de red	50/60 Hz

DIMENSIONES Y PESO

Diámetro	21,5 mm
Peso del producto	6,58 g

Vida media

Vida media	0 relevant
------------	------------

DATOS ADICIONALES DEL PRODUCTO

Contenido mercurio	0.0 mg
Pie de pág. usado solo para el producto	No apto para L 70 W / Los arrancadores están disponibles en dos diseños diferentes, con idénticas características técnicas

PRESTACIONES

Regulable	No
-----------	----

Categorizaciones específicas de país

Referencia para pedido	ST 111
------------------------	--------

Datos de regulación de etiquetado energético (EU 2019/2015)

Largo	40.30 mm
Altura (luminarias incluidas)	21,5 mm
Ancho (incl. Luminarias redondas)	21.50 mm

DATOS LOGÍSTICOS

Código de producto	Cantidad por caja (unidad/master)	Dimensiones (longitud x largo x altura)	Peso bruto	Volumen
4050300064000	Blíster 2	140 mm x 24 mm x 105 mm	34.09 g	0.35 dm³
4050300119588	Embalaje de envío 20	165 mm x 154 mm x 150 mm	321.27 g	3.81 dm³

El codigo de producto mencionado describe la cantidad minima de unidades que puede ser comprada. Una unidad de transporte puede contener uno o más productos individuales. Cuando se realiza la compra, para las cantidades porfavor ingrese una o varias unidades de envío.

Oops! An Error Occurred

The server returned a "500 Internal Server Error".

Something is broken. Please let us know what you were doing when this error occurred. We will fix it as soon as possible. Sorry for any inconvenience caused.

DESCARGO DE RESPONSABILIDAD

Sujeto a cambio sin aviso. Errores y omisiones exceptuadas. Asegurese de utilizar la version más reciente.

Oops! An Error Occurred

The server returned a "500 Internal Server Error".

Something is broken. Please let us know what you were doing when this error occurred. We will fix it as soon as possible. Sorry for any inconvenience caused.