



- Monitor energy consumption per building, floor or room
- Remote control of your Smart Lighting project
- Control any type of DALI luminaire via Smart Switch, Smart Sensor or Smart Web Interface
- Scheduler: automatically turn on/off luminaires at a specific time or date
- Connect multiple Smart Projects into one big project
- Fully compatible with the existing OPPLE Smart Lighting luminaires and accessories







## **Specifications**

Item Code	Item Description
560000005700	Smart Connect Box

<b>Technical Specifications</b>	
Power consumption	Max 14W
Finishing	Grey
Protection Class	II
Communication	Wired: Ethernet (RJ45), DALI, RS-485
	Wireless: Bluetooth® Low Energy Mesh
Integrated DALI power supply	Yes

Electrical Supply	
Nominal voltage	220-240 V AC
Frequency	50/60 Hz
Output voltage	16 V DC
Output current	Max 0.2A

Ambient Conditions	
Operating temperature	-20~+40°C
Storage environment	-25~+50°C







## Dimensional drawing (mm)





