



- Compact BLE to DALI converter for use in OPPLE Smart Lighting System
- Integrate any brand of DALI luminaire into the OPPLE Smart Lighting System
- Control of up to 64 DALI luminaires with Smart Switch or Smart App (DALI Broadcast commands)
- Compatible with OPPLE Smart Sensors & OPPLE Smart Switch
- Very easy to set up with the OPPLE Smart Lighting App, or Smart Connect Box through the web user interface
- Complete wireless communication via Bluetooth® Low Energy (BLE)





Specifications

Item Code	Item Description
821017001300	LEDSmart-BLE-DALI-Converter

Technical Specifications	
IP-class	IP20
Protection	II
Finishing	White RAL9003
Communication	Opple Bluetooth® Low Energy Mesh
Dimming method	DALI Broadcast
Integrated DALI power supply	Yes

Mechanical Properties		
Material housing	PC	

Electrical Supply	
Nominal voltage	220-240 V AC
Frequency	50 Hz
Connection cable	0.75mm^2
Cable Length	12 cm

Electrical Supply	
Nominal voltage	220-240 V AC
Frequency	50 Hz
Connection cable	0.75mm^2
Cable Length	12 cm

Ambient conditions		
Application Temperature	+25°C	
Operating Temperature	-20~+45°C	

	'EARS VARRANTY
--	-------------------



Dimensional drawing (mm)





