

PRODUCT DATASHEET

SMART+ WIFI MULTI POWER SOCKET EU

SMART+ MULTI POWER SOCKET EU | WiFi Multi Power Socket with smart 3 EU sockets and USB ports



Areas of application

- Wherever non-smart devices need to be integrated into compatible smart home systems
- USB ports available for power supply

Product benefits

- Smart Multi power socket: Simple connection of electric devices via smart sockets and smart USB ports
- High standard of safety: Overload protection, Surge protection
- Energy meter: Monitors energy usage of connected devices and tracks the energy consumption
- Integrates conventional electric equipment into compatible smart home systems
- Enables switching of conventional light sources and other electric devices

Product features

- Controllable via LEDVANCE SMART+ App (with minimum Android 8.0 or iOS 14.0)
- Controllable via LEDVANCE SMART+ WiFi Remote Controller
- Controllable via voice control available: Google Assistant or Amazon Alexa
- Smart 3 standard sockets and smart 4 USB ports for charging (2 ports each Type A and C)
- Power sockets can be controlled individually and USB ports are controlled as one group
- Energy meter
- Scheduling
- 1.5 m power cable for flexible installation




- High switching power: up to 3,680 W / 16 A

TECHNICAL DATA

Electrical data

Nominal voltage	230 V
Mains frequency	50 Hz

Dimensions & Weight



Product weight	570.00 g
Length	350 mm
Width	65 mm
Height	40 mm

Lifespan

Number of switching cycles	100000
----------------------------	--------

Colors & materials

Product color	White
Body material	Plastic

Temperatures & operating conditions

Ambient temperature range	-10...+35 °C
---------------------------	--------------

Capabilities

Compatible smart home technology	Amazon Alexa / Google Assistant
----------------------------------	---------------------------------

Certificates & Standards

Protection class	I
Type of protection	IP20

EQUIPMENT / ACCESSORIES

- For control via LEDVANCE SMART+ App, a smartphone or tablet is required (with minimum Android 8.0 or iOS 14.0)

Safety advice

- Disconnect devices which generate heat from the mains, i.e. from the SMART+ Multi Power Socket, after use in order to avoid them being accidentally switched on.
- Very high capacitive and inductive loads may in some cases lead to destruction of the device or reduction in the number of switching cycles.
- Do not use the SMART+ Multi Power Socket in conjunction with medical equipment.
- To be connected to an automatic circuit breaker (max. 16 A).

DOWNLOAD DATA

Documents and certificates



Installation guide



Declarations Of Conformity CE

LOGISTICAL DATA

Product code	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Gross weight	Volume
4058075594784	Folding box 1	87 mm x 94 mm x 378 mm	669.00 g	3.09 dm ³
4058075594791	Shipping box 4	387 mm x 196 mm x 190 mm	2960.00 g	14.41 dm ³

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

References / Links

- Further information and frequently asked questions (FAQs) at www.ledvance.com/consumer/smart/faq

DISCLAIMER

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.