## Double dimming control for Niko Home Control, bronze

## 123-51046

This push button allows you to dim two light points or light circuits. It is attached to the wall-mounted printed circuit board via a click mechanism. Switch including button. Finishing colour: bronze.

## **Technical data**

Double dimming control for Niko Home Control, bronze.

- Material central plate: The central plate is enamelled and made of rigid PC and ASA.
- Print: Arrows printed on the top and bottom keys show whether you are dimming up or down On the middle key(s) a lamp is printed indicating the favourite button. If you press this key the lighting automatically goes to the set dim level.
- Colour: enamelled bronze (approximately NCS S 5005 Y20R, RAL 080 50 05)
- Fire safety
  - The plastic parts of the central plate are self-extinguishing (comply with a filament test of 650°C)
- The plastic parts of the central plate are halogen-free.
- Input voltage: 26 Vdc (SELV, safety extra-low voltage)
- Dismantling: To dismount simply pull the central plate off the base.
- Impact resistance: After mounting, an impact-resistance of IK06 is guaranteed.
- Dimensions (HxWxD): 44.5 x 44.5 x 8.6 mm
- Marking: CE



~	^
:Ċ:	:Ċ:
~	$\sim$

4 year warrant



23-51046 - 07-02-20

www.niko.eu