


# Product datasheet

Specifications



## TeSys integral - auxiliary contact - 4 NO + 1 NC

LA1LC012

⚠ Discontinued on: 21 Feb 2023

EAN Code: 3389110180121

⚠ Discontinued

### Main

Range	TeSys
Device short name	LA1LC
Product or component type	Auxiliary contact

### Complementary

Range compatibility	TeSys TeSys Integral contactor breaker
Mounting location	Right side
Auxiliary contacts operation	Instantaneous
Pole contact composition	2 NO + 1 NC for contactor state 1 NO for tripped 1 NO for tripped on short-circuit
[Ui] rated insulation voltage	690 V
[Ith] conventional free air thermal current	6 A
Connections - terminals	Screw clamp terminals 2 cable(s) 1.5 mm <sup>2</sup> Screw clamp terminals 1 cable(s) 2.5 mm <sup>2</sup>
Net weight	0.22 kg

### Environment

Environmental characteristic	Standard environment
------------------------------	----------------------

### Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	3.000 cm
Package 1 Width	18.000 cm
Package 1 Length	12.500 cm
Package 1 Weight	284.900 g
Unit Type of Package 2	S02
Number of Units in Package 2	18
Package 2 Height	15.000 cm
Package 2 Width	30.000 cm
Package 2 Length	40.000 cm

---

Package 2 Weight 5.382 kg

## Contractual warranty

---

Warranty 18 months


## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better

 <b>Materials and Substances</b>	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	Yes
<a href="#">EU RoHS Directive</a>	Compliant

### Use Again

 <b>Repack and remanufacture</b>	
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins