

Product datasheet

Specifications



red cap marked STOP for circular pushbutton Ø22

Local distributor code:

237147150

ZBA434

EAN Code: 3389110090925

Main

Accessory / separate part category	Marking accessory
Accessory / separate part type	Marked push-button cap
Accessory / separate part destination	Push-button head
User language	English
Marking	White STOP
Cap/operator or lens colour	Red
Shape of signaling unit head	Round
Quantity per set	Set of 1
Sale per indivisible quantity	10
Net weight	0.001 kg

Complementary

Range compatibility	Harmony XB5 Harmony XAL Harmony XB4
Operator profile	Flush
Main group	Push-button

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	1.500 cm
Package 1 Width	2.500 cm
Package 1 Length	2.500 cm
Package 1 Weight	1.200 g
Unit Type of Package 2	BB1
Number of Units in Package 2	10
Package 2 Height	4.500 cm
Package 2 Width	3.400 cm
Package 2 Length	5.400 cm
Package 2 Weight	18.000 g
Unit Type of Package 3	S02

Number of Units in Package 3	550
Package 3 Height	15.000 cm
Package 3 Width	30.000 cm
Package 3 Length	40.000 cm
Package 3 Weight	1.325 kg

Logistical informations

Country of origin	FR
--------------------------	----

Contractual warranty

Warranty	18 months
-----------------	-----------



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

Total lifecycle Carbon footprint 1

Environmental Disclosure [Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard Yes

Packaging without single use plastic Yes

[EU RoHS Directive](#) Pro-active compliance (Product out of EU RoHS legal scope)

REACH Regulation [REACH Declaration](#)

Use Again

Repack and remanufacture

Recyclability potential, in % 0

End of life manual availability No need of specific recycling operations

Take-back No