## **EL1200MS**

## LED Enclosure light with socket and movement sensor



## **CONNECT AND PROTECT**



**Description:** LED enclosure light specially designed for nVent HOFFMAN enclosures. Fast and tool-free assembly thanks to a latching hook system designed to fit the 25mm hole pattern on nVent HOFFMAN enclosures. May be fitted horizontally or vertically.

Lamp type: LED.

Luminosity: 1200 lm.

Light colour: 4000 K (neutral white).

Power consumption:  $12\,\mathrm{W}$ 

 $\label{eq:connection: operating voltage: 100 V - 240 V ~, 50/60 Hz}$   $\label{eq:connection: Infeed, 3-pole. Through wiring, 3-pole.}$ 

Operating temperature:  $-20 \,^{\circ}\text{C} ... +55 \,^{\circ}\text{C}$ 

Protection: IP20

Follow-up time of the motion detector: 120 s

**Dimensions:**  $364 \times 76 \times 48$  mm.

Operating voltage	Socket type	Width	Item no.
100V-240V~, 50/60 Hz	Type F (Shucko)	364	EL1200MS
100V-240V~, 50/60 Hz	Type E	364	EL1200MS-BF
100V-240V~, 50/60 Hz	Type J	364	EL1200MS-CH
100V-240V~, 50/60 Hz	Type G	364	EL1200MS-GB
100 V - 125 V ~, 50/60 Hz	Type B	364	EL1200MS-US