

# EMERGENCY REX EXIT BOX



## REX 3.5W MAINTAINED SLIM EXIT BOX

- Slim LED Exit box 29mm deep
- 2 sets of LEDs arrays: exit and critical area illumination
- Provided with a switched live terminal for maintained or non maintained operation
- Loop-in/ loop-out push in terminals
- Key hole fixing positions for quick installation
- Warranty of 5 years for the fitting, 2 years for the standard battery and 3 years for Self test battery
- Self Test version using LiFePO<sub>4</sub> battery

	Standard	Self test	DIMENSIONS (mm)	Length	Height	Depth
<b>REX4P0-01</b>	<b>REX4P0LST-01</b>					
<b>Comparable to:</b>	8W T8	8W T8	REX4P0-01	395	199	29
<b>Total Power (W):</b>	3.6	3.1	REX4P0LST-01	395	199	29
<b>Total Light Output (lm):</b>	25/40 emergency	35/70 emergency				
<b>Lifetime (hrs):</b>	30,000	50,000				
<b>Beam Angle (deg):</b>	100/200	100/200				
<b>Lux at 1m (lux):</b>	8/15 emergency	8/16 emergency				
<b>CCT (K):</b>	6500	6500				
<b>CRI (Ra):</b>	80	80				
<b>Power Factor (PF):</b>	0.5	0.5				
<b>Impacting Rating (IK):</b>	08	08				
<b>Weight (kg):</b>	0.83	0.89				
<b>Box Qty:</b>	1	1				

