


Item Image




Wiring



Dimensions

Hamilton®

HARTLAND CFX
1 GANG 10A TRIPLE
POLE ROCKER SWITCH



79C TP BL-B

Hartland CFX Antique Brass 1 gang 10A Triple Pole Rocker. Standard Insert will be Black with a Black surround.

Primary Range	Hartland CFX
Insert Type	Triple Pole Fan Isolators
Plate Finish	Antique Brass
Frame Finish	
Switch Colour	Black
Body & Switch Trim	Black
Height	Single = 86mm
Width	Single = 86mm
Depth	Single = 5mm
Fixing Hole Centres	Box Fixing = 60.3mm Box Fixing = 60.3mm
Minimum Wall Box Depth	25mm
Wattage	
Switched Poles	Triple
Current Rating	10A
Voltage	220/250V AC
Max load	10 Amp resistive
Contact Gap Minimum	3mm
Terminal Capacity 1	5 x 1mm ²
Terminal Capacity 2	4 x 1.5mm ²
Terminal Capacity 3	1 x 2.5mm ²
Terminal Capacity 4	1 x 4mm ² Multi-Strand
Terminal Capacity 5	1 x 6mm ²
Earth Terminal Capacity 1	5 x 1mm ²
Earth Terminal Capacity 2	4 x 1.5mm ²
Earth Terminal Capacity 3	3 x 2.5mm ²
Earth Terminal Capacity 4	1 x 4mm ² Multi-Strand
Earth Terminal Capacity 5	1 x 6mm ²
Product Class 1	Must be earthed
Ambient Operating Temperature	-5° to +40° C
Recommended Location	Indoor use only
Standard/Approval	BS EN 60669-1
Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445

All products listed conform to current British or European standards and the product information is correct at the time of going to press.

All accessories are manufactured under an accredited BS EN ISO 9001 : 2008 Quality System.

It is the policy of the company to continually improve products as part of our development programme.

Therefore, we reserve the right to alter designs and dimensions without prior notice.

Illustrations and diagrams are reproduced within the limitations of reproductions and printing processes are not binding.

Due to manufacturing processes we cannot guarantee an exact colour match and shadings of certain finishes.

Correct as at August 2012
E&OE