



MPN: NLRA1330A

Product Name: 13A 30ma Complete With 13A Fuse RCD Adaptor Plug-Top

Brand: Newlec

Category: Residual Current Devices

Product Description: The NLRA1330A is a 13A 30mA complete RCD adaptor plug-top with a built-in 13A fuse. It is designed to provide residual current protection for electrical appliances and equipment. This plug-top is manufactured to BS 7071 standards and offers reliable and efficient protection against electrical faults.

Key Features:

- Rated at 230-250V AC
 - Maximum current: 13A
 - Maximum load: 3,120W
 - Trip current rated at 30mA
 - Typical rated speed: 40ms
 - Manufactured to BS 7071
-

Specifications:

- Type of socket outlet: British Standard
- Number of socket outlets: 1
- Method of operation: Rocker
- Mounting direction: Vertical
- Mounting method: Flush mounted

ETIM Class-9.0: Combination switch/wall socket outlet (EC000020)**ETIM Features:**

- Type of socket outlet: British Standard
- Number of socket outlets: 1
- Method of operation: Rocker
- Mounting direction: Vertical
- Mounting method: Flush mounted
- Material: Plastic
- Material qualifier: Halogen free
- Colour: Black
- Nominal voltage (V): 250
- Rated current (A): 13
- Over voltage-/surge protection: True
- Fault current protection: True

Applications:

The NLRA1330A RCD adaptor plug-top is suitable for use in residential, commercial, and industrial environments. It provides an additional layer of safety by detecting and interrupting electrical faults, preventing electric shock and potential damage to equipment.



Unlock exclusive deals and discover a world of innovative solutions by scanning our QR code and visiting Rexel's website today!