


Item Image




Wiring



Dimensions

Hamilton®

HARTLAND 1 GANG 13A DOUBLE POLE SWITCHED SOCKET



72 SS1 SB-B

Hartland Satin Brass 1 gang 13A Switched Socket - Double Pole. Standard Insert will be Satin Brass with a Black surround.

Primary Range	Hartland
Insert Type	Switched Sockets
Plate Finish	Satin Brass
Frame Finish	
Switch Colour	Satin Brass
Body & Switch Trim	Black
Height	Single = 88mm
Width	Single = 88mm
Depth	Single = 5mm
Fixing Hole Centres	Box Fixing = 60.3mm Box Fixing = 60.3mm
Minimum Wall Box Depth	35mm
Wattage	
Switched Poles	Double
Current Rating	13 Amp
Voltage	220/250V AC
Max load	13 Amp
Contact Gap Minimum	3mm
Terminal Capacity 1	4 x 2.5mm ²
Terminal Capacity 2	3 x 4mm ²
Terminal Capacity 3	2 x 6mm ² Multi-Strand
Terminal Capacity 4	1 x 10mm ²
Terminal Capacity 5	
Earth Terminal Capacity 1	4 x 2.5mm ²
Earth Terminal Capacity 2	3 x 4mm ²
Earth Terminal Capacity 3	2 x 6mm ² Multi-Strand
Earth Terminal Capacity 4	1 x 1mm ²
Earth Terminal Capacity 5	
Product Class 1	Must be earthed
Ambient Operating Temperature	-5° to +40° C
Recommended Location	Indoor use only
Standard/Approval	BS 1363
Patents and Trademarks	Trade Mark No. 2344778

All products listed conform to current British or European standards and the product information is correct at the time of going to press.

All accessories are manufactured under an accredited BS EN ISO 9001 : 2008 Quality System.

It is the policy of the company to continually improve products as part of our development programme.

Therefore, we reserve the right to alter designs and dimensions without prior notice.

Illustrations and diagrams are reproduced within the limitations of reproductions and printing processes are not binding.

Due to manufacturing processes we cannot guarantee an exact colour match and shadings of certain finishes.

Correct as at August 2012
E&OE