

PCV36 SERIES - 36W LED DRIVERS



Part Code	PCV1236	PCV2436
Input Voltage	100 ~ 240VAC	100 ~ 240VAC
Input Frequency	47/63Hz	47/63Hz
Power Factor	0.95	0.95
Power	36W	36W
Voltage	12Vdc	24Vdc
Current Range	0 ~ 3A	0 ~ 1.5A
Efficiency	82%	84%
Connections	Screw terminal on I/P & O/P	Screw terminal on I/P & O/P
Weight	130g	130g
Dimensions	L 166 x W 52 x H 24mm	L 166 x W 52 x H 24mm



PCV50 SERIES - 50W LED DRIVERS



Part Code	PCV1250	PCV2450
Input Voltage	100 ~ 240VAC	100 ~ 240VAC
Input Frequency	47/63Hz	47/63Hz
Power Factor	0.95	0.95
Power	50W	48W
Voltage	12Vdc	24Vdc
Current Range	0 ~ 4.2A	0 ~ 2A
Efficiency	82%	84%
Connections	Screw terminal on I/P & O/P	Screw terminal on I/P & O/P
Weight	300g	300g
Dimensions	L 184 x W 61 x H 32mm	L 184 x W 61 x H 32mm



PCV36 & PCV50 Series 36W & 50W Drivers Mechanical

